

|                 |                              |           |
|-----------------|------------------------------|-----------|
| <b>Produkt:</b> | <b>LL STAGE CYC 5C RGBAW</b> |           |
| Soft ID1:       | C52                          | Hw: 342   |
| Soft ID2:       | -----                        | Hw: ----- |

### DMX channels:

#### Mode1 8b-6ch (+3ch): Dip2=Off

Ch 1 = Red  
Ch 2 = Green  
Ch 3 = Blue  
Ch 4 = Amber  
Ch 5 = White  
Ch 6 = Master ( if Dip3 = On )  
Ch 7 = Strobo ( if Dip3 = On )  
Ch 8 = Fade ( if Dip3 = On )

#### Mode2 16b-12 ch (+3ch): Dip2=On

Ch 1 = Red H (High)  
Ch 2 = Red L (Low)  
Ch 3 = Green H  
Ch 4 = Green L  
Ch 5 = Blue H  
Ch 6 = Blue L  
Ch 7 = Amber H  
Ch 8 = Amber L  
Ch 9 = White H  
Ch 10 = White L  
Ch 11 = Master H ( if Dip3 = On )  
Ch 12 = Master L ( if Dip3 = On )  
Ch 13 = Strobo ( if Dip3 = On )

### Extention and control functions:

DipBCD = 000 = DMX address 001  
DipBCD = 001 – 512 = DMX address 001 – 512  
DipBCD = 9xx = AutoRun1 ( 4s/2s 10steps R, G, B, A, W, N, RB, RA, GB, AW )  
DipBCD = 8xx = AutoRun2 ( 4s/2s 5steps R, G, B, A, W )  
DipBCD = 7xx = AutoRun3 ( 0,5s/0s 10steps R, G, B, A, W, N, RB, RA, GB, AW )  
DipBCD = 6xx = AutoRun4 ( 0,5s/0s 5steps R, G, B, A, W, N )

Dip1 = On = future  
Dip3 = On = add channels: Master, Strobo, Fade(only for Mode 8b)  
Dip4 = Off = Standard curve for Mode 8b  
Dip4 = On = UltraSoft curve for Mode 8b