

<b>Produkt:</b>	<b>LL STAGE CYC 2C AW</b>	
Soft ID1:	C22	Hw: 342
Soft ID2:	-----	Hw: -----

## DMX channels:

### Mode1 8b-6ch (+3ch): Dip2=Off

Ch 1 = Amber                       Ch 3 = Master ( if Dip3 = On )  
 Ch 2 = White                       Ch 4 = Strobo ( if Dip3 = On )  
   Ch 5 = Fade ( if Dip3 = On )

### Mode2 16b-12 ch (+3ch): Dip2=On

Ch 1 = Amber H (High)           Ch 5 = Master H ( if Dip3 = On )  
 Ch 2 = Amber L (Low)           Ch 6 = Master L ( if Dip3 = On )  
 Ch 3 = White H                   Ch 7 = Strobo ( if Dip3 = On )  
 Ch 4 = White L

## Extention and control functions:

DipBCD = 000                       = DMX address 001  
 DipBCD = 001 – 512               = DMX address 001 – 512  
 DipBCD = 9xx                       = AutoRun1  
 DipBCD = 8xx                       = AutoRun2  
 DipBCD = 7xx                       = AutoRun3  
 DipBCD = 6xx                       = AutoRun4

Dip1 = On                           = future  
 Dip3 = On                           = add channels: Master, Strobo, Fade(only for Mode 8b)  
 Dip4 = Off                           = Standard curve for Mode 8b  
 Dip4 = On                           = UltraSoft curve for Mode 8b